A3-RD 3 inch Remodel LED Housing

Catalog #		Prepared by		
Project		Date		
Notes				




3" Remodel Non-IC Housing



- 1) Die-formed aluminum for maximum heat dissipation and rust protection
- 2) Desinged for remodel installations
- 3) Housing can be installed in 1/2" to 1-3/8" thick ceilings.
- 4) Housing is Non-IC rated must be kept at least 3" away form insulation

Junction Box

- 1) ETL listed for through branch wiring
- 2) 2 in-2 out or 4 in-4 out J-box for your better choices
- 3) Designed for straight through conduit runs
- 4) 1/2" and 3/4" romex wiring knockouts



Order Matrix

. E

С

D

Item No.:A3-RD

A Series
A3-RD 3"/Remodel Non-IC Housing

B Input Voltage 120V

Lamp

LED GU10 Lamp 8W max. MR16 GU5.3 8W Max. PAR16 E26 8W Max.

CRI>80%

PF>0.9

Color Temperature:2800K-6500K

D	Wattage	
L3	LED 3W	

L8 LED 8W

Listing

ETL listed for damp location W/Feed through

Other Special requirement please confirm with factory

35K 3500K

50K 5000K

60K 6000K

Email: Sales@accentdesignconcepts.com

Accent Design Concepts

3" TRIM OPTICS



B3001/3 inch Baffle Trim

Lamp: MR16 LED GU5.3 8W Max. GU10 LED GU10 8W Max. PAR16 LED E26 8W Max.



B3006/3 inch Wall Washer Trim

Lamp: MR16 LED GU5.3 8W Max.
GU10 LED GU10 8W Max.
PAR16 LED E26 8W Max.



B3008/3 inch Gimbal Trim

Lamp: MR16 LED GU5.3 8W Max. GU10 LED GU10 8W Max. PAR16 LED E26 8W Max.



B3002/3 inch Reflector Trim

Lamp: MR16 LED GU5.3 8W Max. GU10 LED GU10 8W Max. PAR16 LED E26 8W Max.



B3007/3 inch Gimbal Ring Trim

Lamp: MR16 LED GU5.3 8W Max. GU10 LED GU10 8W Max. PAR16 LED E26 8W Max.



B3802/3 inch Shower with Frosted Lens

Lamp: MR16 LED GU5.3 6W Max. GU10 LED GU10 6W Max. PAR16 LED E26 6W Max.



B3011/3 inch Square Trim

Lamp: MR16 LED GU5.3 8W Max. GU10 LED GU10 8W Max. PAR16 LED E26 8W Max.



BS3002/3 inch Square Reflector Trim

Lamp: MR16 LED GU5.3 8W Max. GU10 LED GU10 8W Max. PAR16 LED E26 8W Max.



BS3001/3 inch Square Baffle Trim

Lamp: MR16 LED GU5.3 8W Max. GU10 LED GU10 8W Max. PAR16 LED E26 8W Max.



BS3007/3 inch Square Gimbal Trim

Lamp: MR16 LED GU5.3 8W Max. GU10 LED GU10 8W Max. PAR16 LED E26 8W Max.

